

## CUSTOMIZE PARAMETERS

### HINT:

The followings are the possible items to be customized.

### NOTICE:

- After confirming whether the items of the customer's request are applicable or not for the customized items, perform the customize operation.
- Be sure to record the current value before customizing.
- In case of performing the troubleshooting, pay attention as there is a possibility that the function is OFF by customizing. (Example: In case of the symptom in which "The wireless operation does not function", check that the wireless operation is not OFF by customizing, then perform the troubleshooting.)

### ILLUMINATED ENTRY

DISPLAY(ITEM)	DEFAULT	CONTENTS	SETTING
I/L ON / UNLOCK (Interior lamp ON w/ door key unlock)	ON	Function to light up the interior lamp*, ignition lamp and step lamp when unlocking with the door key cylinder. *: Interior lamp comes on when the interior lamp switch is at the DOOR position.	ON / OFF
LIGHTING TIME (Lighting Time)	15 s	To change the lighting time after closing the door. (It will quickly fade out in case of turning the ignition ON.)	7.5 s / 15 s / 30 s

### LIGHT CONTROL

#### HINT:

Sensitivity adjustment can hardly be confirmed. Please check by customer's actual driving.

DISPLAY(ITEM)	DEFAULT	CONTENTS	SETTING
SENSITIVITY (Turn ON luminous intensity)	NORMAL	To adjust the sensitivity of the lighting illumination. Refer to the *1 illustration.	DARK2 / DARK1 / NORMAL / LIGHT1 / LIGHT2
LIGHT CTRL TYPE (Control Type)	CURRENT	To change the control logic when the light control switch is in the AUTO position. Refer to the *2 illustration.	CURRENT / OLD

#### Illustration of \*1

Lighting brightness	Dark ←————→ Bright
Setting	DARK2 ——— DARK1 ——— NORMAL ——— LIGHT1 ——— LIGHT2

#### Illustration of \*2

	Brightness of the surrounding when lighting	Lighting delay	Delay of turning light off	**2
OLD	Old logic	6 sec.	6 sec.	3 sec.
CURRENT	New logic **1 ('97/8-)	15 sec.	15 sec.	15 sec.

\*\*1: The new one has the logic to light up two times brighter than the old logic.

\*\*2: Delay time until the headlamp is turned on when it suddenly gets dark.